Robust Series

650VA/1200VA

USER'S MANUAL



User's Manual R650/R1200



Uninterruptible Power System

Safety - CAUTION

- This UPS utilizes voltages that may be hazardous. Do not attempt to disassemble the unit. The unit contains no user serviceable parts. Only factory service personnel may perform repairs.
- Internal battery voltage is 12Vdc (650VA) or 24V (1200VA). Sealed, lead-acid, 6 cells battery.
- Connection to any other type of receptacle other than a two-pole, three-wire grounded receptacle may result in shock hazard as well as violate local electrical codes.
- In the event of an emergency, press the OFF button and disconnect the power cord from the AC power supply to properly disable the UPS.
- Do not allow liquids or any foreign object to enter the UPS. Do not place beverages or any other liquid-containing vessels on or near the unit.
- This unit intended for installation in a controlled environment (temperature controlled, indoor area free of conductive contaminants).
 Avoid installing the UPS in locations where there is standing or running water, or excessive humidity.
- Do not plug the UPS input into its own output.
- Do not attach a power strip or surge suppressor to the UPS.
- Do not attach non-computer-related items, such as medical equipment, life-support equipment, microwave ovens, or vacuum cleaners to UPS
- To reduce the risk of overheating the UPS, do not cover the UPS' cooling vents and avoid exposing the unit to direct sunlight or installing the unit near heat emitting appliances such as space heaters or furnaces.
- Unplug the UPS prior to cleaning and do not use liquid or spray detergent.
- Do not dispose of batteries in a fire as they may explode.
- Do not open or mutilate the battery or batteries. Released electrolyte is harmful to the skin and eyes. It may be toxic.
- A battery can present a risk of electrical shock and high short circuit current. The following precautions should be observed when working on batteries:
- 1) Remove watches, rings, or other metal objects from the hands.
- 2) Use tools with insulated handles.
- 3) Wear rubber gloves and boots.

- 4) Do not lay tools or metal parts on top of batteries.
- Disconnect charging source prior to connecting or disconnecting batteries terminals.
- Servicing of batteries should be performed or supervised by personnel knowledgeable of batteries and the required precautions.
 Keep unauthorized personnel away from batteries.
- When replacing batteries, replace with the same number and type of sealed lead-acid battery. The maximum ambient temperature rating is 40°C
- This pluggable type equipment with battery already installed by the supplier is operator installable and may be operated by laymen.
- During the installation of this equipment it should be assured that the sum of the leakage currents of the UPS and the connected loads does not exceed 3.5mA.
- Attention, hazardous through electric shock. Also with disconnection
 of this unit from the mains, hazardous voltage still may be accessible
 through supply from battery. The battery supply should be therefore
 disconnected in the plus and minus pole of the battery when
 maintenance or service work inside the UPS is necessary.
- The mains socket outlet that supplies the UPS shall be installed near the UPS and shall be easily accessible.

INTRODUCTION

This UPS is specially designed for Personal Computer with multi-functions. Its light weight, compact design perfect fits to the limited working environment. The line of UPS is equipped with boost and buck AVR to stabilize input voltage range. It is also built-in with Do start function. This function enables the UPS to be started up without AC power supplied. Although it's a small UPS, The main features of UPS are listed below:


- Microprocessor control guarantees high reliability.
- Equipped with Boost and Buck AVR.
- DC Start Function.
- Auto restart while AC recovery.
- Compact size, Light Weight.
- Provides AC Overload protection.


TROUBLE SHOOTING

Symptom	Possible Cause	Remedy	
No LED display on	Battery weak.	1. Charge battery up to 8 hours	
the front panel.	Battery defect.	2. Replace with the same type of battery.	
	Power switch is not pressed.	3. Press the power switch again.	
Alarm buzzer beeps continuously when AC supply is normal.	Overload of the UPS.	Verify that the load matches the UPS capability specified in the spec.	
When power failure, back-up time is	Overload of the UPS.	Remove some noncritical load.	
shorten.	Battery voltage is too low.	Charge battery 8 hours or more.	
	Battery defect due to high temperature operation environment, or improper operation to battery.	Replace with the same type of battery.	
Mains normal but LED is flashing.	Power cord is loose.	Reconnect the power cord properly.	

If any abnormal situations occur that are not listed above, please call service people immediately.

SYSTEM DESCRIPTION






1. Inspection

Remove the UPS from its packaging and inspect it for damage that may have occurred during shipping. If any damage is discovered, repack the unit and return it to the place of purchase.

2. Charging

This unit is shipped from the factory with its internal battery fully charged, however, some charge may be lost during shipping and the battery

should be recharged prior to use. Plug the unit into an appropriate power supply and allow the UPS to charge fully by leaving it plugged in for at least 6 hours with no load (no electrical devices such as computers, monitors, etc.) connected.




3. Placement

Install the UPS unit in any protected environment that provides adequate airflow around the unit, and is free from excessive dust, corrosive fumes and conductive contaminants. Do not operate your UPS in an environment where the ambient temperature or humidity is high.




On the other hand, place the UPS away from the monitor at least 20cm to avoid interference.




4. Connection

Plug the UPS into a 2-pole, 3-wire grounded receptacle. Then connect one computer-related device into each of the power receptacles supplied on the back of the UPS.



5. Turn On/Off

To turn on the UPS unit, press the power switch lightly. To turn off the UPS unit, press the power switch again.



6. DC Start

The UPS is equipped with DC Start. To start the UPS when AC utility power is not available, simply press the power switch.

SPECIFICATION

MODEL		R650	R1200	
CAPACITY	VA/W	650VA/360W	1200VA/600W	
INPUT	Voltage	230VAC		
	Voltage Range	140-300VAC		
	Frequency	>40Hz (Auto Sensing)		
ОИТРИТ	Voltage	230VAC		
	Voltage Regulation	+/-10%		
	(Batt. Mode)			
	Frequency	50Hz		
	Frequency Regulation	+/-1 Hz		
	(Batt. Mode)			
	Output Waveform	Modified Sinewave		
BATTERY	Battery Type	12V7Ah x 1	12V7Ah x 2	
	Backup Time (at a PC	10-15 minutes	30-35 minutes	
	load with 15" monitor)			
	Recharge Time	6 hours to 90% after complete		
	, , , , , , , , , , , , , , , , , , ,	discharge		
TRANSFER TIME	Typical	4-8 ms		
NDICATOR	AC Mode	Green lighting	Green lighting	
	Battery Mode	Yellow flashing	Yellow flashing	
	Fault Mode	Red lighting	Red lighting	
AUDIBLE ALARM	Backup Mode	Sounding every 10 seconds		
	Low Battery	Sounding every second		
	Overload	Sounding every 0.5 second		
	Fault	Continuously sounding		
PROTECTION	Full Protection	Discharge, overcharge, and overload		
		protection		
PHYSICAL	Dimension (mm), DXWXH	278X100X143	365x139x195	
WEIGHT	Net Weight	4.4kgs	9.2kgs	
ENVIRONMENT	Operating	0- 40°C, 0-90 % relative humidity		
	Environment	(non-condensing)		
	Noise Level	Less than 40dB		

SANTAK ELECTRONIC (SHENZHEN) CO.,LTD

No.8 Baoshi Rd, Block 72 Baoan, Shenzhen,

Guangdong, China

www.eaton.com www.santak.com